



Table of Contents

Purchase Order Acknowledgment2
 Interchange Control Header.....4
 Functional Group Header.....6
 Transaction Set Header.....8
 Beginning Segment for Purchase Order Acknowledgment.....9
 Reference Information.....11
 Administrative Communications Contact.....12
 F.O.B. Related Instructions.....14
 Terms of Sale/Deferred Terms of Sale.....15
 Date/Time Reference.....16
 Loop N9.....17
 Extended Reference Information.....18
 Text.....19
 Loop N1.....20
 Party Identification.....21
 Party Location.....22
 Geographic Location.....23
 Loop PO1.....24
 Baseline Item Data.....25
 Loop PID.....28
 Product/Item Description.....29
 Item Physical Details.....30
 Loop ACK.....31
 Line Item Acknowledgment.....32
 Loop SLN.....34
 Subline Item Detail.....35
 Product/Item Description.....38
 Loop CTT.....39
 Transaction Totals.....40
 Transaction Set Trailer.....41
 Functional Group Trailer.....42
 Interchange Control Trailer.....43

855

Purchase Order Acknowledgment

Functional Group=PR

This X12 Transaction Set contains the format and establishes the data contents of the Purchase Order Acknowledgment Transaction Set (855) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to a seller's acknowledgment of a buyer's purchase order. This transaction set can also be used as notification of a vendor generated order. This usage advises a buyer that a vendor has or will ship merchandise as prearranged in their partnership.

Not Defined:

Pos	Id	Segment Name	Req	Max Use	Repeat	Notes	Usage
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

Heading:

Pos	Id	Segment Name	Req	Max Use	Repeat	Notes	Usage
0100	ST	Transaction Set Header	M	1			Must use
0200	BAK	Beginning Segment for Purchase Order Acknowledgment	M	1			Must use
0500	REF	Reference Information	M	1			Must use
0600	PER	Administrative Communications Contact	O	1			Used
0800	FOB	F.O.B. Related Instructions	O	1			Used
1300	ITD	Terms of Sale/Deferred Terms of Sale	O	1			Used
1500	DTM	Date/Time Reference	O	3		N1/1500	Used
LOOP ID - N9					1	N1/2800L	
2800	N9	Extended Reference Information	M	1			Must use
2900	MTX	Text	M	1			Must use
LOOP ID - N1					1		
3000	N1	Party Identification	O	1			Used
3200	N3	Party Location	O	2			Used
3300	N4	Geographic Location	O	1			Used

Detail:

Pos	Id	Segment Name	Req	Max Use	Repeat	Notes	Usage
LOOP ID - PO1					100000	N2/0100L	
0100	PO1	Baseline Item Data	O	1		N2/0100	Used
LOOP ID - PID					3		
0500	PID	Product/Item Description	O	1			Used
0900	PO4	Item Physical Details	O	1			Used
LOOP ID - ACK					104		
2700	ACK	Line Item Acknowledgment	O	1			Used
LOOP ID - SLN					1000		
4900	SLN	Subline Item Detail	O	1			Used

5100	PID	Product/Item Description	O	3	Used
------	---------------------	--------------------------	---	---	------

Summary:

Pos	Id	Segment Name	Req	Max Use	Repeat	Notes	Usage
LOOP ID - CTT							
0100	CTT	Transaction Totals	O	1	1	N3/0100L	Used
0300	SE	Transaction Set Trailer	M	1			Must use

Not Defined:

Pos	Id	Segment Name	Req	Max Use	Repeat	Notes	Usage
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

Notes:

- 1/1500 If any Dates are sent on the 850 PO, those must be sent back on the 855. Otherwise, all are Optional.
- 1/2800L Optional Loop.

If sent, then N9 & MTX segments are required.
- 2/0100L PO102 is required.
- 2/0100 PO102 is required.
- 3/0100L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.
- 3/0100 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Must use

Description: Code identifying the type of information in the Authorization Information

<u>Code</u>	<u>Name</u>
00	No Authorization Information Present (No Meaningful Information in I02)

ISA02	I02	Authorization Information	M	AN	10/10	Must use
-------	-----	----------------------------------	---	----	-------	----------

Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)

ISA03	I03	Security Information Qualifier	M	ID	2/2	Must use
-------	-----	---------------------------------------	---	----	-----	----------

Description: Code identifying the type of information in the Security Information

<u>Code</u>	<u>Name</u>
00	No Security Information Present (No Meaningful Information in I04)

ISA04	I04	Security Information	M	AN	10/10	Must use
-------	-----	-----------------------------	---	----	-------	----------

Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)

ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use
-------	-----	---------------------------------	---	----	-----	----------

Description: Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified
All valid standard codes are used.

ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use
-------	-----	------------------------------	---	----	-------	----------

Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element

ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use
-------	-----	---------------------------------	---	----	-----	----------

Description: Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified
All valid standard codes are used.

ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use
-------	-----	--------------------------------	---	----	-------	----------

Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them

ISA09 I08 **Interchange Date** M DT 6/6 Must use

Description: Date of the interchange

ISA10 I09 **Interchange Time** M TM 4/4 Must use

Description: Time of the interchange

ISA11 I65 **Repetition Separator** M 1/1 Must use

Description: Type is not applicable; the repetition separator is a delimiter and not a data element; this field provides the delimiter used to separate repeated occurrences of a simple data element or a composite data structure; this value must be different than the data element separator, component element separator, and the segment terminator

ISA12 I11 **Interchange Control Version Number** M ID 5/5 Must use

Description: Code specifying the version number of the interchange control segments

<u>Code</u>	<u>Name</u>
00501	Standards Approved for Publication by ASC X12 Procedures Review Board through October 2003

ISA13 I12 **Interchange Control Number** M N0 9/9 Must use

Description: A control number assigned by the interchange sender

ISA14 I13 **Acknowledgment Requested** M ID 1/1 Must use

Description: Code indicating sender's request for an interchange acknowledgment

<u>Code</u>	<u>Name</u>
0	No Interchange Acknowledgment Requested

ISA15 I14 **Interchange Usage Indicator** M ID 1/1 Must use

Description: Code indicating whether data enclosed by this interchange envelope is test, production or information

<u>Code</u>	<u>Name</u>
P	Production Data

ISA16 I15 **Component Element Separator** M 1/1 Must use

Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator

GS Functional Group Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use

To indicate the beginning of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code	M	ID	2/2	Must use

Description: Code identifying a group of application related transaction sets

<u>Code</u>	<u>Name</u>
PR	Purchase Order Acknowledgment (855)

GS02	142	Application Sender's Code	M	AN	2/15	Must use
------	-----	----------------------------------	---	----	------	----------

Description: Code identifying party sending transmission; codes agreed to by trading partners

GS03	124	Application Receiver's Code	M	AN	2/15	Must use
------	-----	------------------------------------	---	----	------	----------

Description: Code identifying party receiving transmission; codes agreed to by trading partners

GS04	373	Date	M	DT	8/8	Must use
------	-----	-------------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

GS05	337	Time	M	TM	4/8	Must use
------	-----	-------------	---	----	-----	----------

Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)

GS06	28	Group Control Number	M	N0	1/9	Must use
------	----	-----------------------------	---	----	-----	----------

Description: Assigned number originated and maintained by the sender

GS07	455	Responsible Agency Code	M	ID	1/2	Must use
------	-----	--------------------------------	---	----	-----	----------

Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480

<u>Code</u>	<u>Name</u>
X	Accredited Standards Committee X12

GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use
------	-----	---	---	----	------	----------

Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level

of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed

<u>Code</u>	<u>Name</u>
005010	Standards Approved for Publication by ASC X12 Procedures Review Board through October 2003

Semantics:

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use

Description: Code uniquely identifying a Transaction Set

<u>Code</u>	<u>Name</u>
855	Purchase Order Acknowledgment

ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
------	-----	--------------------------------	---	----	-----	----------

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

BAK Beginning Segment for Purchase Order Acknowledgment

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 5

User Option (Usage): Must use

To indicate the beginning of the Purchase Order Acknowledgment Transaction Set and transmit identifying numbers and dates

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
BAK01	353	Transaction Set Purpose Code	M	ID	2/2	Must use

Description: Code identifying purpose of transaction set

Code	Name
00	Original

BAK02	587	Acknowledgment Type	M	ID	2/2	Must use
-------	-----	---------------------	---	----	-----	----------

Description: Code specifying the type of acknowledgment

Code	Name
AC	Acknowledge - With Detail and Change
AD	Acknowledge - With Detail, No Change
AE	Acknowledge - With Exception Detail Only
AK	Acknowledge - No Detail or Change
RD	Reject with Detail
RJ	Rejected - No Detail

BAK03	324	Purchase Order Number	M	AN	1/22	Must use
-------	-----	-----------------------	---	----	------	----------

Description: Identifying number for Purchase Order assigned by the orderer/purchaser

BAK04	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

BAK05	328	Release Number	O	AN	1/30	Used
-------	-----	----------------	---	----	------	------

Description: Number identifying a release against a Purchase Order previously placed by the parties involved in the transaction

Semantics:

1. BAK04 is the date assigned by the purchaser to purchase order.
2. BAK08 is the seller's order number.
3. BAK09 is the date assigned by the sender to the acknowledgment.

REF Reference Information

Pos: 0500	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To specify identifying information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

<u>Code</u>	<u>Name</u>
IA	Internal Vendor Number

REF02	127	Reference Identification	M	AN	1/50	Must use
-------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

PER Administrative Communications Contact

Pos: 0600	Max: 1
Heading - Optional	
Loop: N/A	Elements: 8

User Option (Usage): Used

To identify a person or office to whom administrative communications should be directed

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
PER01	366	Contact Function Code	M	ID	2/2	Must use
Description: Code identifying the major duty or responsibility of the person or group named						
		<u>Code</u>	<u>Name</u>			
		IC	Information Contact			
PER02	93	Name	M	AN	1/60	Must use
Description: Free-form name						
PER03	365	Communication Number Qualifier	X	ID	2/2	Used
Description: Code identifying the type of communication number						
		<u>Code</u>	<u>Name</u>			
		TE	Telephone			
PER04	364	Communication Number	X	AN	1/256	Used
Description: Complete communications number including country or area code when applicable						
PER05	365	Communication Number Qualifier	X	ID	2/2	Used
Description: Code identifying the type of communication number						
		<u>Code</u>	<u>Name</u>			
		FX	Facsimile			
PER06	364	Communication Number	X	AN	1/256	Used
Description: Complete communications number including country or area code when applicable						
PER07	365	Communication Number Qualifier	X	ID	2/2	Used
Description: Code identifying the type of communication number						
		<u>Code</u>	<u>Name</u>			
		EM	Electronic Mail			
PER08	364	Communication Number	X	AN	1/256	Used

Description: Complete communications number including country or area code when applicable

Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.
2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

FOB F.O.B. Related Instructions

Pos: 0800	Max: 1
Heading - Optional	
Loop: N/A	Elements: 3

User Option (Usage): Used

To specify transportation instructions relating to shipment

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
FOB01	146	Shipment Method of Payment	M	ID	2/2	Must use

Description: Code identifying payment terms for transportation charges

<u>Code</u>	<u>Name</u>
CC	Collect
CF	Collect, Freight Credited Back to Customer
DF	Defined by Buyer and Seller
MX	Mixed
PC	Prepaid but Charged to Customer
PP	Prepaid (by Seller)

FOB02	309	Location Qualifier	X	ID	1/2	Used
-------	-----	---------------------------	---	----	-----	------

Description: Code identifying type of location

<u>Code</u>	<u>Name</u>
DE	Destination (Shipping)
OR	Origin (Shipping Point)

FOB03	352	Description	O	AN	1/80	Used
-------	-----	--------------------	---	----	------	------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. C0302 - If FOB03 is present, then FOB02 is required.
2. C0405 - If FOB04 is present, then FOB05 is required.
3. C0706 - If FOB07 is present, then FOB06 is required.
4. C0809 - If FOB08 is present, then FOB09 is required.

Semantics:

1. FOB01 indicates which party will pay the carrier.
2. FOB02 is the code specifying transportation responsibility location.
3. FOB06 is the code specifying the title passage location.
4. FOB08 is the code specifying the point at which the risk of loss transfers. This may be different than the location specified in FOB02/FOB03 and FOB06/FOB07.

ITD

Terms of Sale/Deferred Terms of Sale

Pos: 1300	Max: 1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

To specify terms of sale

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ITD01	336	Terms Type Code	O	ID	2/2	Used

Description: Code identifying type of payment terms

<u>Code</u>	<u>Name</u>
01	Basic
41	Letter of Credit
45	Bank Transfer

ITD12	352	Description	O	AN	1/80	Used
-------	-----	-------------	---	----	------	------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. L03040513 - If ITD03 is present, then at least one of ITD04, ITD05 or ITD13 is required.
2. L08040513 - If ITD08 is present, then at least one of ITD04, ITD05 or ITD13 is required.
3. L091011 - If ITD09 is present, then at least one of ITD10 or ITD11 is required.

Comments:

1. If the code in ITD01 is "04", then ITD07 or ITD09 is required and either ITD10 or ITD11 is required; if the code in ITD01 is "05", then ITD06 or ITD07 is required.

DTM Date/Time Reference

Pos: 1500	Max: 3
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use

Description: Code specifying type of date or time, or both date and time

<u>Code</u>	<u>Name</u>
001	Cancel After
002	Delivery Requested
010	Requested Ship

DTM02	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

Loop N9

Pos: 2800	Repeat: 1
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2800	N9	Extended Reference Information	M	1		Must use
2900	MTX	Text	M	1		Must use

N9 Extended Reference Information

Pos: 2800	Max: 1
Heading - Mandatory	
Loop: N9	Elements: 2

User Option (Usage): Must use

To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use
Description: Code qualifying the Reference Identification						
		Code	Name			
		L1	Letters or Notes			
N903	369	Free-form Description	M	AN	1/45	Must use
Description: Free-form descriptive text						

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

MTX Text

Pos: 2900	Max: 1
Heading - Mandatory	
Loop: N9	Elements: 1

User Option (Usage): Must use

To specify textual data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MTX02	1551	Textual Data	O	AN	1/4096	Used

Description: To transmit large volumes of message text

Syntax Rules:

1. C0102 - If MTX01 is present, then MTX02 is required.
2. C0302 - If MTX03 is present, then MTX02 is required.
3. C0504 - If MTX05 is present, then MTX04 is required.

Semantics:

1. MTX05 is the number of lines to advance before printing.

Comments:

1. If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Loop N1

Pos: 3000	Repeat: 1
Optional	
Loop: N1	Elements: N/A

User Option (Usage): Used

To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3000	N1	Party Identification	O	1		Used
3200	N3	Party Location	O	2		Used
3300	N4	Geographic Location	O	1		Used

N1 Party Identification

Pos: 3000	Max: 1
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

<u>Code</u>	<u>Name</u>
MP	Manufacturing Plant

N102	93	Name	X	AN	1/60	Used
------	----	-------------	---	----	------	------

Description: Free-form name

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Party Location

Pos: 3200	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used

To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use
		Description: Address information				
N302	166	Address Information	O	AN	1/55	Used
		Description: Address information				

N4 Geographic Location

Pos: 3300	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Used

To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
		Description: Free-form text for city name				
N402	156	State or Province Code	X	ID	2/2	Used
		Description: Code (Standard State/Province) as defined by appropriate government agency				
N403	116	Postal Code	O	ID	3/15	Used
		Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				
N404	26	Country Code	O	ID	2/3	Used
		Description: Code identifying the country				

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. N402 is required only if city name (N401) is in the U.S. or Canada.

Loop PO1

Pos: 0100	Repeat: 100000
Optional	
Loop: PO1	Elements: N/A

User Option (Usage): Used

To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	PO1	Baseline Item Data	O	1		Used
0500		Loop PID	O		3	Used
0900	PO4	Item Physical Details	O	1		Used
2700		Loop ACK	O		104	Used
4900		Loop SLN	O		1000	Used

PO1 Baseline Item Data

Pos: 0100	Max: 1
Detail - Optional	
Loop: PO1	Elements: 18

User Option (Usage): Used

To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	O	AN	1/20	Used
Description: Alphanumeric characters assigned for differentiation within a transaction set						
PO102	380	Quantity	X	R	1/15	Used
Description: Numeric value of quantity						
PO103	355	Unit or Basis for Measurement Code	O	ID	2/2	Used
Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken						
		<u>Code</u>	<u>Name</u>			
		AS	Assortment			
		EA	Each			
PO104	212	Unit Price	X	R	1/17	Used
Description: Price per unit of product, service, commodity, etc.						
PO106	235	Product/Service ID Qualifier	X	ID	2/2	Used
Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)						
		<u>Code</u>	<u>Name</u>			
		SK	Stock Keeping Unit (Long SKU)			
PO107	234	Product/Service ID	X	AN	1/48	Used
Description: Identifying number for a product or service						
PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used
Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)						
		<u>Code</u>	<u>Name</u>			
		CB	Buyer's Catalog Number			
		UP	UCC - 12			

VN Vendor's (Seller's) Item Number

PO109 234 **Product/Service ID** X AN 1/48 Used

Description: Identifying number for a product or service

PO110 235 **Product/Service ID Qualifier** X ID 2/2 Used

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

<u>Code</u>	<u>Name</u>
CB	Buyer's Catalog Number
UP	UCC - 12
VN	Vendor's (Seller's) Item Number

PO111 234 **Product/Service ID** X AN 1/48 Used

Description: Identifying number for a product or service

PO112 235 **Product/Service ID Qualifier** X ID 2/2 Used

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

<u>Code</u>	<u>Name</u>
CB	Buyer's Catalog Number (Short SKU)
UP	UCC - 12
VN	Vendor's (Seller's) Item Number

PO113 234 **Product/Service ID** X AN 1/48 Used

Description: Identifying number for a product or service

PO114 235 **Product/Service ID Qualifier** X ID 2/2 Used

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

<u>Code</u>	<u>Name</u>
PG	Packaging Specification Number

PO115 234 **Product/Service ID** X AN 1/48 Used

Description: Identifying number for a product or service

PO116 235 **Product/Service ID Qualifier** X ID 2/2 Used

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

<u>Code</u>	<u>Name</u>
C3	Classification

PO117 234 **Product/Service ID** X AN 1/48 Used

Description: Identifying number for a product or service

PO118	235	Product/Service ID Qualifier	X	ID	2/2	Used
-------	-----	-------------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

<u>Code</u>	<u>Name</u>
IT	Buyer's Style Number

PO119	234	Product/Service ID	X	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Semantics:

1. PO102 is quantity ordered.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Loop PID

Pos: 0500	Repeat: 3
Optional	
Loop: PID	Elements: N/A

User Option (Usage): Used

To describe a product or process in coded or free-form format

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0500	PID	Product/Item Description	O	1		Used

PID Product/Item Description

Pos: 0500	Max: 1
Detail - Optional	
Loop: PID	Elements: 3

User Option (Usage): Used

To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use

Description: Code indicating the format of a description

<u>Code</u>	<u>Name</u>
F	Free-form

PID02	750	Product/Process Characteristic Code	O	ID	2/3	Used
-------	-----	--	---	----	-----	------

Description: Code identifying the general class of a product or process characteristic

<u>Code</u>	<u>Name</u>
08	Product
74	Vendor size description
75	Buyer's Color Description

PID05	352	Description	M	AN	1/80	Must use
-------	-----	--------------------	---	----	------	----------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Comments:

1. If PID01 equals "F", then PID05 is used.

PO4 Item Physical Details

Pos: 0900	Max: 1
Detail - Optional	
Loop: PO1	Elements: 1

User Option (Usage): Used

To specify the physical qualities, packaging, weights, and dimensions relating to the item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO401	356	Pack	O	N0	1/6	Used

Description: The number of inner containers, or number of eaches if there are no inner containers, per outer container

Syntax Rules:

1. P0203 - If either PO402 or PO403 is present, then the other is required.
2. C0506 - If PO405 is present, then PO406 is required.
3. P0607 - If either PO406 or PO407 is present, then the other is required.
4. P0809 - If either PO408 or PO409 is present, then the other is required.
5. C1013 - If PO410 is present, then PO413 is required.
6. C1113 - If PO411 is present, then PO413 is required.
7. C1213 - If PO412 is present, then PO413 is required.
8. L13101112 - If PO413 is present, then at least one of PO410, PO411 or PO412 is required.
9. C1716 - If PO417 is present, then PO416 is required.
10. C1804 - If PO418 is present, then PO404 is required.

Semantics:

1. PO415 is used to indicate the relative layer of this package or range of packages within the layers of packaging. Relative Position 1 (value R1) is the innermost package.
2. PO416 is the package identifier or the beginning package identifier in a range of identifiers.
3. PO417 is the ending package identifier in a range of identifiers.
4. PO418 is the number of packages in this layer.

Comments:

1. PO403 - The "Unit or Basis for Measure Code" in this segment position is for purposes of defining the unit of measure of the "Size" identified in the PO402. For example: If the carton contains 24 12-Ounce packages, it would be described as follows: Data element 356 = "24"; Data element 357 = "12"; Data element 355 = "OZ".
2. PO413 defines the unit of measure for PO410, PO411, and PO412.

Loop ACK

Pos: 2700	Repeat: 104
Optional	
Loop: ACK	Elements: N/A

User Option (Usage): Used

To acknowledge the ordered quantities and specify the ready date for a specific line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2700	ACK	Line Item Acknowledgment	O	1		Used

User Note 1:

If the PO1 Loop is sent, at least one ACK loop is also required.

ACK Line Item Acknowledgment

Pos: 2700	Max: 1
Detail - Optional	
Loop: ACK	Elements: 5

User Option (Usage): Used

To acknowledge the ordered quantities and specify the ready date for a specific line item

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
ACK01	668	Line Item Status Code	M	ID	2/2	Must use

Description: Code specifying the action taken by the seller on a line item requested by the buyer

Code	Name
DR	Item Accepted - Date Rescheduled
IA	Item Accepted
IB	Item Backordered
IH	Item on Hold
IP	Item Accepted - Price Changed
IQ	Item Accepted - Quantity Changed
IR	Item Rejected
IS	Item Accepted - Substitution Made
R2	Item Rejected, Invalid Item Product Number

ACK02	380	Quantity	X	R	1/15	Used
-------	-----	----------	---	---	------	------

Description: Numeric value of quantity

ACK03	355	Unit or Basis for Measurement Code	X	ID	2/2	Used
-------	-----	------------------------------------	---	----	-----	------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

Code	Name
AS	Assortment
EA	Each

ACK04	374	Date/Time Qualifier	C	ID	3/3	Used
-------	-----	---------------------	---	----	-----	------

Description: Code specifying type of date or time, or both date and time

Code	Name
068	Current Schedule Ship

ACK05	373	Date	X	DT	8/8	Used
-------	-----	------	---	----	-----	------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Syntax Rules:

1. P0203 - If either ACK02 or ACK03 is present, then the other is required.
2. C0405 - If ACK04 is present, then ACK05 is required.
3. P0708 - If either ACK07 or ACK08 is present, then the other is required.
4. P0910 - If either ACK09 or ACK10 is present, then the other is required.
5. P1112 - If either ACK11 or ACK12 is present, then the other is required.
6. P1314 - If either ACK13 or ACK14 is present, then the other is required.
7. P1516 - If either ACK15 or ACK16 is present, then the other is required.
8. P1718 - If either ACK17 or ACK18 is present, then the other is required.
9. P1920 - If either ACK19 or ACK20 is present, then the other is required.
10. P2122 - If either ACK21 or ACK22 is present, then the other is required.
11. P2324 - If either ACK23 or ACK24 is present, then the other is required.
12. P2526 - If either ACK25 or ACK26 is present, then the other is required.
13. P2728 - If either ACK27 or ACK28 is present, then the other is required.
14. C282729 - If ACK28 is present, then ACK27 and ACK29 are required.

Semantics:

1. ACK29 Industry Reason Code may be used to identify the item status. In addition, it may be used in conjunction with ACK01 to further clarify the status.

User Note 1:

If ACK01=IB or DR, ACK04 and ACK05 are required

If ACK01=IB or IQ, ACK02 and ACK03 are required

If ACK01=IP, the new price for this item must be sent in PO104

If ACK01=IS, the substitute Vendor Item Number must be sent in PO109

If ACK01=R2, the corrected product number should be sent in PO107/09/11/13/15, depending which product number was incorrect

Loop SLN

Pos: 4900	Repeat: 1000
Optional	
Loop: SLN	Elements: N/A

User Option (Usage): Used

To specify product subline detail item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
4900	SLN	Subline Item Detail	O	1		Used
5100	PID	Product/Item Description	O	3		Used

SLN Subline Item Detail

Pos: 4900	Max: 1
Detail - Optional	
Loop: SLN	Elements: 19

User Option (Usage): Used

To specify product subline detail item data

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
SLN01	350	Assigned Identification	M	AN	1/20	Must use
Description: Alphanumeric characters assigned for differentiation within a transaction set						
SLN03	662	Relationship Code	M	ID	1/1	Must use
Description: Code indicating the relationship between entities						
		<u>Code</u>	<u>Name</u>			
		I	Included			
SLN04	380	Quantity	X	R	1/15	Used
Description: Numeric value of quantity						
SLN05	C001	Composite Unit of Measure	X	Comp		Used
Description: To identify a composite unit of measure (See Figures Appendix for examples of use)						
Comments:						
1. If C001-02 is not used, its value is to be interpreted as 1.						
2. If C001-03 is not used, its value is to be interpreted as 1.						
3. If C001-05 is not used, its value is to be interpreted as 1.						
4. If C001-06 is not used, its value is to be interpreted as 1.						
5. If C001-08 is not used, its value is to be interpreted as 1.						
6. If C001-09 is not used, its value is to be interpreted as 1.						
7. If C001-11 is not used, its value is to be interpreted as 1.						
8. If C001-12 is not used, its value is to be interpreted as 1.						
9. If C001-14 is not used, its value is to be interpreted as 1.						
10. If C001-15 is not used, its value is to be interpreted as 1.						
	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use
Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken						
		<u>Code</u>	<u>Name</u>			
		AS	Assortment			
SLN06	212	Unit Price	X	R	1/17	Used
Description: Price per unit of product, service, commodity, etc.						
SLN09	235	Product/Service ID Qualifier	X	ID	2/2	Used

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

<u>Code</u>	<u>Name</u>
SK	Stock Keeping Unit (Long SKU)

SLN10	234	Product/Service ID	X	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

SLN11	235	Product/Service ID Qualifier	X	ID	2/2	Used
-------	-----	-------------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

<u>Code</u>	<u>Name</u>
UP	UCC - 12

SLN12	234	Product/Service ID	X	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

SLN13	235	Product/Service ID Qualifier	X	ID	2/2	Used
-------	-----	-------------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

<u>Code</u>	<u>Name</u>
VN	Vendor's (Seller's) Item Number

SLN14	234	Product/Service ID	X	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

SLN15	235	Product/Service ID Qualifier	X	ID	2/2	Used
-------	-----	-------------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

<u>Code</u>	<u>Name</u>
CB	Buyer's Catalog Number (Short SKU)

SLN16	234	Product/Service ID	X	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

SLN17	235	Product/Service ID Qualifier	X	ID	2/2	Used
-------	-----	-------------------------------------	---	----	-----	------

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

<u>Code</u>	<u>Name</u>
PG	Packaging Specification Number

SLN18	234	Product/Service ID	X	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service

SLN19	235	Product/Service ID Qualifier	X	ID	2/2	Used
Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)						
		Code	Name			
		C3	Classification			
SLN20	234	Product/Service ID	X	AN	1/48	Used
Description: Identifying number for a product or service						
SLN21	235	Product/Service ID Qualifier	X	ID	2/2	Used
Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)						
		Code	Name			
		IT	Buyer's Style Number			
SLN22	234	Product/Service ID	X	AN	1/48	Used
Description: Identifying number for a product or service						

Syntax Rules:

1. P0405 - If either SLN04 or SLN05 is present, then the other is required.
2. C0706 - If SLN07 is present, then SLN06 is required.
3. C0806 - If SLN08 is present, then SLN06 is required.
4. P0910 - If either SLN09 or SLN10 is present, then the other is required.
5. P1112 - If either SLN11 or SLN12 is present, then the other is required.
6. P1314 - If either SLN13 or SLN14 is present, then the other is required.
7. P1516 - If either SLN15 or SLN16 is present, then the other is required.
8. P1718 - If either SLN17 or SLN18 is present, then the other is required.
9. P1920 - If either SLN19 or SLN20 is present, then the other is required.
10. P2122 - If either SLN21 or SLN22 is present, then the other is required.
11. P2324 - If either SLN23 or SLN24 is present, then the other is required.
12. P2526 - If either SLN25 or SLN26 is present, then the other is required.
13. P2728 - If either SLN27 or SLN28 is present, then the other is required.

Semantics:

1. SLN01 is the identifying number for the subline item.
2. SLN02 is the identifying number for the subline level. The subline level is analogous to the level code used in a bill of materials.
3. SLN03 is the configuration code indicating the relationship of the subline item to the baseline item.
4. SLN08 is a code indicating the relationship of the price or amount to the associated segment.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. SLN01 is related to (but not necessarily equivalent to) the baseline item number. Example: 1.1 or 1A might be used as a subline number to relate to baseline number 1.
3. SLN09 through SLN28 provide for ten different product/service IDs for each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

PID

Product/Item Description

Pos: 5100	Max: 3
Detail - Optional	
Loop: SLN	Elements: 3

User Option (Usage): Used

To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use

Description: Code indicating the format of a description

<u>Code</u>	<u>Name</u>
F	Free-form

PID02	750	Product/Process Characteristic Code	O	ID	2/3	Used
-------	-----	--	---	----	-----	------

Description: Code identifying the general class of a product or process characteristic

<u>Code</u>	<u>Name</u>
08	Product
74	Vendor size description
75	Buyer's Color Description

PID05	352	Description	M	AN	1/80	Must use
-------	-----	--------------------	---	----	------	----------

Description: A free-form description to clarify the related data elements and their content

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Comments:

1. If PID01 equals "F", then PID05 is used.

Loop CTT

Pos: 0100	Repeat: 1
Optional	
Loop: CTT	Elements: N/A

User Option (Usage): Used

To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	CTT	Transaction Totals	0	1		Used

CTT Transaction Totals

Pos: 0100	Max: 1
Summary - Optional	
Loop: CTT	Elements: 1

User Option (Usage): Used

To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

Description: Total number of line items in the transaction set

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

SE Transaction Set Trailer

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	NO	1/10	Must use

Description: Total number of segments included in a transaction set including ST and SE segments

SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
------	-----	---------------------------------------	---	----	-----	----------

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Comments:

1. SE is the last segment of each transaction set.

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included	M	N0	1/6	Must use

Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element

GE02	28	Group Control Number	M	N0	1/9	Must use
------	----	-----------------------------	---	----	-----	----------

Description: Assigned number originated and maintained by the sender

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups	M	N0	1/5	Must use
Description: A count of the number of functional groups included in an interchange						
IEA02	I12	Interchange Control Number	M	N0	9/9	Must use
Description: A control number assigned by the interchange sender						