

The Consolidated Edison Company of New York 867 Monthly Usage Supplemental Information

1. Email Correspondence to Discontinue

Once an E/M is on EDI for a particular transaction, Con Edison will no longer allow any communication via email from / to E/M related to that transaction. Con Edison systems that currently receive and process E/M emails will reject emails where E/Ms are EDI qualified for that particular transaction. Rejection notification will be sent back via email.
2. BPT Beginning Segment for Product Transfer and Resale

For cancellations of previously reported usage, Con Edison will send a separate transaction containing the cancelled usage. The BPT01 element will always = 01 for these cancel usage transactions. The BPT09 element in these cancel transactions will always will always contain the unique transaction ID located in BPT02 in the transaction that is being cancelled.
3. DTM Date / Time Reference (Next Meter Read Date)

Con Edison will always provide the date of the customers next scheduled meter read.
4. N1 Name (E/M/Marketer) / E/M Name

On 867 Monthly Usage Transactions, Con Edison will provide the E/M Name as it appears in Con Edison files.
5. N1 Name (Customer) / Customer Name

On 867 Monthly Usage Transactions, Con Edison will provide the Customer Name as it appears on the Con Edison account. Note: In Con Edison systems, the Customer Account Name (Customer Name) has a length of 21 characters. Con Edison also maintains, as necessary, a Customer Name Overflow of 42 characters. The combined total length of Customer Account Name and Customer Name Overflow is 63 characters. In N102, Con Edison will provide the concatenated value of Customer Account Name and Customer Name Overflow. This combined total of 63 characters is 3 characters larger than that which is permitted by the N102 data element (60). Thus, the name overflow could be truncated, though in Con Edison's experience, a Name Overflow is seldom greater than 39 characters and thus truncation of the Name Overflow is very unlikely.

The Consolidated Edison Company of New York 867 Monthly Usage Supplemental Information

- | | |
|--|---|
| 6. N3 Address Information & N4 Geographic Location (Service Address) | Service address will be provided at Con Edison on 867 Monthly Usage Transactions. |
| 7. REF Reference Identification (ESCO/ Marketer Customer Account Number) | Not used at Con Edison on 867 Monthly Usage Transactions. |
| 8. REF Reference Identification (Previous Utility Account Number) / Reference Identification | Con Edison will provide the Previous Utility Account Number on 867 Monthly Usage Transactions, where the account number has changed in the last 90 days. |
| 9. PTD Product Transfer and Resale Detail (Metered Summary) | At Con Edison, on 867 Monthly Usage Transactions the PTD – BO loop (Metered Summary) for all accounts with metered services. The loop will contain the summary usage information for the account. |

Note: At Con Edison, an account may have Time of Use billing, where the time of use measurements for kilowatthours and/or demand are not associated with specific meters. For these accounts Time of Use billing information will be included only in the PTD – BO loop (Metered Summary).

Accounts can be identified as Time of Use billing by referring to the Time of Use codes listed in REF (Rate Sub Class), as well as service class 116, 117, or 118. E/M's can obtain a description of Con Edison's "Time of Day Codes" via Con Edison's Retail Access Website at <http://www.coned.com/retailaccess>.

The Consolidated Edison Company of New York 867 Monthly Usage Supplemental Information

10. REF Reference Identification (Rate Sub Class) / Reference Identification
- On 867 Monthly Usage Transactions, Con Edison will send the Rate Sub Class in the BO, BC, and BQ PTD loops for electric accounts. Not used for monthly usage of gas accounts.
- Con Edison uses this field to indicate whether the account is High or Low Tension or Both, provides a DC (direct current) indicator where “Y” means DC and “N” means AC, and also displays a two digit code which indicates whether the account has Time of Use billing. Format is: HI or LO or BO for both, space Y or N space ## (two digit Time of Day Code). Example, HI N 54 means that the service characteristics are high tension AC and Time of Day Code = 54. E/M’s can obtain a description of Con Edison’s “Time of Day Codes” via Con Edison’s Retail Access Website at <http://www.coned.com/retailaccess>.
11. AMT Monetary Amount (Backout Credit)
- Not used at Con Edison on 867 Monthly Usage Transactions.

The Consolidated Edison Company of New York 867 Monthly Usage Supplemental Information

12. MEA Measurements / MEA07 At Con Edison, additional Measurement Significance Codes are needed to correctly describe electric usage. Con Edison uses the following Measurement Significance Codes in 867 Electric Historical Usage Responses:
- 41 = Small Time of Day Off Peak Energy
 - 42 = Small Time of Day On Peak Energy
 - 51 = Total Energy or Total Billed Demand
 - 84 = High Tension On Peak Energy
 - 85 = High Tension Off Peak Energy
 - 86 = Low Tension On Peak Energy
 - 87 = Low Tension Off Peak Energy
 - 88 = Low Tension Total Energy
 - 89 = Low Tension Primary Demand
 - 90 = Low Tension Secondary Demand
 - 91 = Low Tension Transmission Demand
 - 92 = High Tension Total Energy
 - 93 = High Tension Primary Demand
 - 94 = High Tension Transmission Demand
13. PTD Product Transfer and Resale Detail (Unmetered Usage) At Con Edison, on 867 Monthly Usage Responses the PTD – BC loop (Unmetered Usage) is sent when the account has unmetered service points. The loop will contain the unmetered usage history data for the account.

The Consolidated Edison Company of New York 867 Monthly Usage Supplemental Information

14. PTD Product Transfer and Resale Detail (Metered Consumption Detail) At Con Edison, on 867 Historical Usage Responses the PTD – BQ loop (Metered Consumption Detail) is sent for all accounts that have metered service points. The loop will contain the historical usage by meter.
- Note:** At Con Edison, an account may have Time of Use billing, where the time of use measurements for kilowatthours and/or demand are not associated with specific meters. For these accounts Time of Use billing information will be included only in the PTD – BO loop (Metered Summary).
- Accounts can be identified as Time of Use billing by referring to the Time of Use codes listed in REF (Rate Sub Class), as well as service class 116, 117, or 118. E/M's can obtain a description of Con Edison's "Time of Day Codes" via Con Edison's Retail Access Website at <http://www.coned.com/retailaccess>.
15. PTD Product Transfer and Resale Detail (Interim Bill Notice) Because Con Edison does not support the Utility Bill Ready Model, the PTD- BK loop is not used on 867 Monthly Usage Transactions.
16. PTD Product Transfer and Resale Detail (Metered Usage Detail) Because Con Edison does not support the Single Retailer Model, the PTD- PM loop and all of its segments are not used on 867 Monthly Usage Transactions.