

# **864 Text Message**

**X12/V4060/864: 864 Text Message**

**Version: 6.06**

**Modified: 06/07/2006**

# Table of Contents

<b>864</b>	<b>Text Message</b> .....	<b>1</b>
ISA	Interchange Control Header .....	2
GS	Functional Group Header .....	5
ST	Transaction Set Header .....	7
BMG	Beginning Segment For Text Message .....	8
MIT	Loop MIT .....	9
MIT	Message Identification .....	10
MSG	Message Text .....	11
SE	Transaction Set Trailer .....	12
GE	Functional Group Trailer .....	13
IEA	Interchange Control Trailer .....	14

# 864 Text Message

## Functional Group=TX

This X12 Transaction Set contains the format and establishes the data content of the Text Message Transaction Set (864) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide users with a capability to electronically move messages, contracts, explanations, and other one-time communications. It is the intent of this transaction set to provide electronic communication (messages) for people, not for computer processing. The use of the transaction set to transmit quasi or unique transaction set standards is discouraged. The use of the Text Message transaction set demands of the sender certain detailed information about the recipient. The transaction set's purpose is to provide communication to the recipient in some human-readable form. The recipient's network will dictate what capabilities are available for delivery of the information. It is the responsibility of the sender to obtain this information and include it in the transmission.

### Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

### Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0100	ST	Transaction Set Header	M	1			Must use
0200	BMG	Beginning Segment For Text Message	M	1			Must use

### Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<b>LOOP ID - MIT</b>					<b>&gt;1</b>		
0100	MIT	Message Identification	M	1			Must use
0800	MSG	Message Text	M	>1			Must use

### Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0100	SE	Transaction Set Trailer	M	1			Must use

### Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

# ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

**User Option (Usage):** Must use

To start and identify an interchange of zero or more functional groups and interchange-related control segments

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	<b>Authorization Information Qualifier</b>	M	ID	2/2	Must use
		<b>Description:</b> Code identifying the type of information in the Authorization Information				
		<b>Code Name</b>				
		00 No Authorization Information Present (No Meaningful Information in I02)				
ISA02	I02	<b>Authorization Information</b>	M	AN	10/10	Must use
		<b>Description:</b> Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)				
ISA03	I03	<b>Security Information Qualifier</b>	M	ID	2/2	Must use
		<b>Description:</b> Code identifying the type of information in the Security Information				
		<b>Code Name</b>				
		00 No Security Information Present (No Meaningful Information in I04)				
ISA04	I04	<b>Security Information</b>	M	AN	10/10	Must use
		<b>Description:</b> This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)				
ISA05	I05	<b>Interchange ID Qualifier</b>	M	ID	2/2	Must use
		<b>Description:</b> Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified				
		<b>Code Name</b>				
		14 Duns Plus Suffix				
ISA06	I06	<b>Interchange Sender ID</b>	M	AN	15/15	Must use
		<b>Description:</b> Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element				

		<u>Code</u>	<u>Name</u>				
		0722717110	US Production				
		100					
		0722717111	Canada Production				
		CAP					
ISA07	I05	<b>Interchange ID Qualifier</b>		M	ID	2/2	Must use
<p><b>Description:</b> Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified</p> <p><b>All valid standard codes are used.</b></p>							
ISA08	I07	<b>Interchange Receiver ID</b>		M	AN	15/15	Must use
<p><b>Description:</b> Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them</p>							
ISA09	I08	<b>Interchange Date</b>		M	DT	6/6	Must use
<p><b>Description:</b> Date of the interchange</p>							
ISA10	I09	<b>Interchange Time</b>		M	TM	4/4	Must use
<p><b>Description:</b> Time of the interchange</p>							
ISA11	I65	<b>Repetition Separator</b>		M		1/1	Must use
<p><b>Description:</b> Type is not applicable; the repetition separator is a delimiter and not a data element; this field provides the delimiter used to separate repeated occurrences of a simple data element or a composite data structure; this value must be different than the data element separator, component element separator, and the segment terminator</p>							
		<u>Code</u>	<u>Name</u>				
		:	Colon				
		@	At				
		]	Bracket				
		^	Carrot				
			Pipe				
<p><b>The Home Depot Requirements:</b></p> <p><i>This separator can be any non-alpha-numeric character that is also not used as an element separator, segment terminator or elsewhere in the data.</i></p>							
ISA12	I11	<b>Interchange Control Version Number</b>		M	ID	5/5	Must use
<p><b>Description:</b> Code specifying the version number of the interchange control segments</p>							
		<u>Code</u>	<u>Name</u>				
		00406	Standards Approved for Publication by ASC X12 Procedures Review Board through October 2002				

ISA13	I12	<b>Interchange Control Number</b>	M	N0	9/9	Must use
		<b>Description:</b> A control number assigned by the interchange sender				
ISA14	I13	<b>Acknowledgment Requested</b>	M	ID	1/1	Must use
		<b>Description:</b> Code indicating sender's request for an interchange acknowledgment				
		<b>Code Name</b>				
		0 No Interchange Acknowledgment Requested				
ISA15	I14	<b>Interchange Usage Indicator</b>	M	ID	1/1	Must use
		<b>Description:</b> Code indicating whether data enclosed by this interchange envelope is test, production or information				
		<b>Code Name</b>				
		P Production Data				
ISA16	I15	<b>Component Element Separator</b>	M		1/1	Must use
		<b>Description:</b> Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator				

# GS Functional Group Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

**User Option (Usage):** Must use

To indicate the beginning of a functional group and to provide control information

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	<b>Functional Identifier Code</b>	M	ID	2/2	Must use
		<b>Description:</b> Code identifying a group of application related transaction sets				
		<b>Code Name</b>				
		TX Text Message (864)				
GS02	142	<b>Application Sender's Code</b>	M	AN	2/15	Must use
		<b>Description:</b> Code identifying party sending transmission; codes agreed to by trading partners				
		<b>Code Name</b>				
		072271711 US Production				
		072271711 Canada Production				
		C				
GS03	124	<b>Application Receiver's Code</b>	M	AN	2/15	Must use
		<b>Description:</b> Code identifying party receiving transmission; codes agreed to by trading partners				
GS04	373	<b>Date</b>	M	DT	8/8	Must use
		<b>Description:</b> Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year				
GS05	337	<b>Time</b>	M	TM	4/8	Must use
		<b>Description:</b> Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)				
GS06	28	<b>Group Control Number</b>	M	NO	1/9	Must use
		<b>Description:</b> Assigned number originated and maintained by the sender				
GS07	455	<b>Responsible Agency Code</b>	M	ID	1/2	Must use
		<b>Description:</b> Code identifying the issuer of				

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
		the standard; this code is used in conjunction with Data Element 480				
		<b><u>Code</u> <u>Name</u></b>				
		X Accredited Standards Committee X12				
GS08	480	<b>Version / Release / Industry Identifier Code</b>	M	AN	1/12	Must use
		<b>Description:</b> Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed				
		<b><u>Code</u> <u>Name</u></b>				
		004060 Standards Approved for Publication by ASC X12 Procedures Review Board through October 2002				

**Semantics:**

1. GS04 is the group date.
2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

**Comments:**

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.



# ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

**User Option (Usage):** Must use

To indicate the start of a transaction set and to assign a control number

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	<b>Transaction Set Identifier Code</b>	M	ID	3/3	Must use
		<b>Description:</b> Code uniquely identifying a Transaction Set				
		<b>Code Name</b>				
		864 Text Message				
ST02	329	<b>Transaction Set Control Number</b>	M	AN	4/9	Must use
		<b>Description:</b> Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

## Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

# BMG Beginning Segment For Text Message

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

**User Option (Usage):** Must use

To indicate the beginning of a Text Message Transaction Set

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BMG01	353	<b>Transaction Set Purpose Code</b>	M	ID	2/2	Must use
		<b>Description:</b> Code identifying purpose of transaction set <b>All valid standard codes are used.</b>				
BMG02	352	<b>Description</b>	O	AN	1/80	Must use
		<b>Description:</b> A free-form description to clarify the related data elements and their content				

## Comments:

1. BMG02 contains the message subject.

# Loop MIT

Pos: 0100	Repeat: >1
Mandatory	
Loop: MIT	Elements: N/A

**User Option (Usage):** Must use

To identify the beginning of a specific message and to allow the identification of a subject for the message

## Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	MIT	Message Identification	M	1		Must use
0800	MSG	Message Text	M	>1		Must use

# MIT Message Identification

Pos: 0100	Max: 1
Detail - Mandatory	
Loop: MIT	Elements: 3

**User Option (Usage):** Must use

To identify the beginning of a specific message and to allow the identification of a subject for the message

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MIT01	127	<b>Reference Identification</b>	M	AN	1/50	Must use
		<b>Description:</b> Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier				
MIT03	931	<b>Page Width</b>	O	N0	1/3	Must use
		<b>Description:</b> Definition of the maximum number of characters per line that can be expected in the message text				
MIT04	932	<b>Page Length Lines</b>	O	N0	1/3	Must use
		<b>Description:</b> Definition of the maximum number of lines per page that can be expected in the message text				

## Semantics:

1. MIT01 contains the message number.
2. MIT02 contains the message subject.

## Comments:

1. MIT03 default is 80 characters.
2. MIT04 default is 66 lines.

# MSG Message Text

Pos: 0800	Max: >1
Detail - Mandatory	
Loop: MIT	Elements: 2

**User Option (Usage):** Must use

To provide a free-form format that allows the transmission of text information

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MSG01	933	<b>Free-form Message Text</b>	M	AN	1/264	Must use
		<b>Description:</b> Free-form message text				
MSG02	934	<b>Printer Carriage Control Code</b>	X	ID	2/2	Must use
		<b>Description:</b> A field to be used for the control of the line feed of the receiving printer				
		<b>Code Name</b>				
		DS	Advance two lines before print			
		NP	Advance to next page before print			
		SS	Advance to new line before print			

## Syntax Rules:

1. C0302 - If MSG03 is present, then MSG02 is required.

## Semantics:

1. MSG03 is the number of lines to advance before printing.

## Comments:

1. MSG02 is not related to the specific characteristics of a printer, but identifies top of page, advance a line, etc.
2. If MSG02 is "AA - Advance the specified number of lines before print" then MSG03 is required.

# SE Transaction Set Trailer

Pos: 0100	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

**User Option (Usage):** Must use

To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	<b>Number of Included Segments</b>	M	NO	1/10	Must use
		<b>Description:</b> Total number of segments included in a transaction set including ST and SE segments				
SE02	329	<b>Transaction Set Control Number</b>	M	AN	4/9	Must use
		<b>Description:</b> Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

## Comments:

1. SE is the last segment of each transaction set.

# GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

**User Option (Usage):** Must use

To indicate the end of a functional group and to provide control information

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	<b>Number of Transaction Sets Included</b>	M	NO	1/6	Must use
		<b>Description:</b> Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element				
GE02	28	<b>Group Control Number</b>	M	NO	1/9	Must use
		<b>Description:</b> Assigned number originated and maintained by the sender				

## Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

## Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

# IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

**User Option (Usage):** Must use

To define the end of an interchange of zero or more functional groups and interchange-related control segments

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	<b>Number of Included Functional Groups</b>	M	N0	1/5	Must use
		<b>Description:</b> A count of the number of functional groups included in an interchange				
IEA02	I12	<b>Interchange Control Number</b>	M	N0	9/9	Must use
		<b>Description:</b> A control number assigned by the interchange sender				