

# **Micro Center**

**X12/V4010/850: Purchase Order**

**Author:**

**SPS Commerce**

# 850 Purchase Order

## Functional Group=PO

This Standard contains the format and establishes the data contents of the Purchase Order Transaction Set (850) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to the placement of purchase orders for goods and services. This transaction set should not be used to convey purchase order changes or purchase order acknowledgment information.

### Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	BEG	Beginning Segment for Purchase Order	M	1			Must use
060	PER	Administrative Communications Contact	O	1			Used
110	CSH	Sales Requirements	O	1			Used
150	DTM	Date/Time Reference	O	3			Used
240	TD5	Carrier Details (Routing Sequence/Transit Time)	O	1			Used
<b>LOOP ID - N9</b>					<b>1</b>		
295	N9	Reference Identification	O	1			Used
300	MSG	Message Text	O	1			Used
<b>LOOP ID - N1</b>					<b>1</b>		
310	N1	Name	M	1			Must use
330	N3	Address Information	M	1			Must use
340	N4	Geographic Location	M	1			Must use

### Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<b>LOOP ID - PO1</b>					<b>100000</b>	<b>N2/010L</b>	
010	PO1	Baseline Item Data	M	1		N2/010	Must use
<b>LOOP ID - CTP</b>					<b>1</b>		
040	CTP	Pricing Information	O	1			Used

### Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<b>LOOP ID - CTT</b>					<b>1</b>	<b>N3/010L</b>	
010	CTT	Transaction Totals	O	1		N3/010	Must use
030	SE	Transaction Set Trailer	M	1			Must use

### Notes:

2/010L PO102 is required.

2/010 PO102 is required.

3/010L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/010 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

# ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

**User Option (Usage):** Must use

To indicate the start of a transaction set and to assign a control number

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	<b>Transaction Set Identifier Code</b>	M	ID	3/3	Must use
<b>Description:</b> Code uniquely identifying a Transaction Set						
<b>Code Name</b>						
850 Purchase Order						
ST02	329	<b>Transaction Set Control Number</b>	M	AN	4/9	Must use
<b>Description:</b> Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

## Semantics:

1. The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).

# BEG Beginning Segment for Purchase Order

Pos: 020	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 4

**User Option (Usage):** Must use

To indicate the beginning of the Purchase Order Transaction Set and transmit identifying numbers and dates

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BEG01	353	<b>Transaction Set Purpose Code</b>	M	ID	2/2	Must use
		<b>Description:</b> Code identifying purpose of transaction set				
		<b>Code Name</b>				
		00 Original				
BEG02	92	<b>Purchase Order Type Code</b>	M	ID	2/2	Must use
		<b>Description:</b> Code specifying the type of Purchase Order				
		<b>Code Name</b>				
		SA Stand-alone Order				
BEG03	324	<b>Purchase Order Number</b>	M	AN	1/22	Must use
		<b>Description:</b> Identifying number for Purchase Order assigned by the orderer/purchaser				
BEG05	373	<b>Date</b>	M	DT	8/8	Must use
		<b>Description:</b> Date expressed as CCYYMMDD				

## Semantics:

1. BEG05 is the date assigned by the purchaser to purchase order.

# PER Administrative Communications Contact

Pos: 060	Max: 1
Heading - Optional	
Loop: N/A	Elements: 4

User Option (Usage): Used

To identify a person or office to whom administrative communications should be directed

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PER01	366	<b>Contact Function Code</b>	M	ID	2/2	Must use
		<b>Description:</b> Code identifying the major duty or responsibility of the person or group named				
		<b>Code Name</b>				
		IC Information Contact				
PER02	93	<b>Name</b>	O	AN	1/35	Used
		<b>Description:</b> Free-form name				
PER03	365	<b>Communication Number Qualifier</b>	X	ID	2/2	Used
		<b>Description:</b> Code identifying the type of communication number				
		<b>Code Name</b>				
		TE Telephone				
PER04	364	<b>Communication Number</b>	X	AN	1/80	Used
		<b>Description:</b> Complete communications number including country or area code when applicable				

## Syntax Rules:

1. P0304 - If either PER03 or PER04 is present, then the other is required.
2. P0506 - If either PER05 or PER06 is present, then the other is required.
3. P0708 - If either PER07 or PER08 is present, then the other is required.

# CSH Sales Requirements

Pos: 110	Max: 1
Heading - Optional	
Loop: N/A	Elements: 1

**User Option (Usage):** Used

To specify general conditions or requirements of the sale

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CSH01	563	Sales Requirement Code	O	ID	1/2	Used

**Description:** Code to identify a specific requirement or agreement of sale

**Code Name**

- N No Back Order
- Y Back Order if Out of Stock

## Syntax Rules:

1. C0203 - If CSH02 is present, then CSH03 is required.
2. P0607 - If either CSH06 or CSH07 is present, then the other is required.
3. P0910 - If either CSH09 or CSH10 is present, then the other is required.

## Semantics:

1. CSH03 is the maximum monetary amount value which the order must not exceed.
2. CSH04 is the account number to which the purchase amount is charged.
3. CSH05 is the date specified by the sender to be shown on the invoice.
4. CSH06 identifies the source of the code value in CSH07.

# DTM Date/Time Reference

Pos: 150	Max: 3
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

To specify pertinent dates and times

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	<b>Date/Time Qualifier</b>	M	ID	3/3	Must use
<b>Description:</b> Code specifying type of date or time, or both date and time						
<b>Code Name</b>						
001 Cancel After						
002 Delivery Requested						
010 Requested Ship						
DTM02	373	<b>Date</b>	M	DT	8/8	Must use
<b>Description:</b> Date expressed as CCYYMMDD						

## Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

# TD5 Carrier Details (Routing Sequence/Transit Time)

Pos: 240	Max: 1
Heading - Optional	
Loop: N/A	Elements: 1

**User Option (Usage):** Used

To specify the carrier and sequence of routing and provide transit time information

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
TD505	387	Routing	X	AN	1/35	Used

**Description:** Free-form description of the routing or requested routing for shipment, or the originating carrier's identity

## Syntax Rules:

1. R0204050612 - At least one of TD502, TD504, TD505, TD506 or TD512 is required.
2. C0203 - If TD502 is present, then TD503 is required.
3. C0708 - If TD507 is present, then TD508 is required.
4. C1011 - If TD510 is present, then TD511 is required.
5. C1312 - If TD513 is present, then TD512 is required.
6. C1413 - If TD514 is present, then TD513 is required.
7. C1512 - If TD515 is present, then TD512 is required.

## Semantics:

1. TD515 is the country where the service is to be performed.

## Comments:

1. When specifying a routing sequence to be used for the shipment movement in lieu of specifying each carrier within the movement, use TD502 to identify the party responsible for defining the routing sequence, and use TD503 to identify the actual routing sequence, specified by the party identified in TD502.

# Loop N9

Pos: 295	Repeat: 1
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

To transmit identifying information as specified by the Reference Identification Qualifier

## Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
295	N9	Reference Identification	O	1		Used
300	MSG	Message Text	O	1		Used

# N9 Reference Identification

Pos: 295	Max: 1
Heading - Optional	
Loop: N9	Elements: 2

**User Option (Usage):** Used

To transmit identifying information as specified by the Reference Identification Qualifier

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	<b>Reference Identification Qualifier</b>	M	ID	2/3	Must use
		<b>Description:</b> Code qualifying the Reference Identification				
		<b>Code Name</b>				
		L1		Letters or Notes		
N903	369	<b>Free-form Description</b>	M	AN	1/45	Must use
		<b>Description:</b> Free-form descriptive text				

## Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

## Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

# MSG Message Text

Pos: 300	Max: 1
Heading - Optional	
Loop: N9	Elements: 1

**User Option (Usage):** Used

To provide a free-form format that allows the transmission of text information

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
MSG01	933	<b>Free-Form Message Text</b>	M	AN	1/264	Must use

**Description:** Free-form message text

## Syntax Rules:

1. C0302 - If MSG03 is present, then MSG02 is required.

## Semantics:

1. MSG03 is the number of lines to advance before printing.

## Comments:

1. MSG02 is not related to the specific characteristics of a printer, but identifies top of page, advance a line, etc.
2. If MSG02 is "AA - Advance the specified number of lines before print" then MSG03 is required.

# Loop N1

Pos: 310	Repeat: 1
Mandatory	
Loop: N1	Elements: N/A

**User Option (Usage):** Must use

To identify a party by type of organization, name, and code

## Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
310	N1	Name	M	1		Must use
330	N3	Address Information	M	1		Must use
340	N4	Geographic Location	M	1		Must use

# N1 Name

<b>Pos: 310</b>	<b>Max: 1</b>
<b>Heading - Mandatory</b>	
<b>Loop: N1</b>	<b>Elements: 4</b>

**User Option (Usage):** Must use

To identify a party by type of organization, name, and code

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	<b>Entity Identifier Code</b>	M	ID	2/3	Must use
<b>Description:</b> Code identifying an organizational entity, a physical location, property or an individual						
<b>Code Name</b>						
ST Ship To						
N102	93	<b>Name</b>	O	AN	1/60	Used
<b>Description:</b> Free-form name						
N103	66	<b>Identification Code Qualifier</b>	M	ID	1/2	Must use
<b>Description:</b> Code designating the system/method of code structure used for Identification Code (67)						
<b>Code Name</b>						
92 Assigned by Buyer or Buyer's Agent						
N104	67	<b>Identification Code</b>	M	AN	2/80	Must use
<b>Description:</b> Code identifying a party or other code						
001 MICRO CENTER, INC.						
#001 DISTRIBUTION CENTER						
2701-B CHARTER STREET						
COLUMUBS, OH 43228						
002 MICRO CENTER, INC.						
#002 DISTRIBUTION CENTER						
2701-B CHARTER STREET						
COLUMUBS, OH 43228						
004 MICRO CENTER, INC.						
#004 DISTRIBUTION CENTER						
2701-B CHARTER STREET						
COLUMUBS, OH 43228						
009 MICRO CENTER, INC.						
DC – CENTER STAGE						
2701-B CHARTER STREET						
COLUMUBS, OH 43228						
501 MICRO CENTER, INC.						
#501 MICRO ELECTRONICS, INC.						
4105 LEAP ROAD, DOCKS #6-14						
HILLIARD, OHIO 43026						
551 MICRO CENTER, INC.						
#551 W/B M/O SELLING						
2701-A CHARTER STREET						
COLUMUBS, OH 43228						

**Syntax Rules:**

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

**Comments:**

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

# N3 Address Information

Pos: 330	Max: 1
Heading - Mandatory	
Loop: N1	Elements: 2

**User Option (Usage):** Must use

To specify the location of the named party

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	<b>Address Information</b>	M	AN	1/55	Must use
		<b>Description:</b> Address information				
N302	166	<b>Address Information</b>	O	AN	1/55	Used
		<b>Description:</b> Address information				

# N4 Geographic Location

Pos: 340	Max: 1
Heading - Mandatory	
Loop: N1	Elements: 3

**User Option (Usage):** Must use

To specify the geographic place of the named party

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	<b>City Name</b>	O	AN	2/30	Used
		<b>Description:</b> Free-form text for city name				
N402	156	<b>State or Province Code</b>	O	ID	2/2	Used
		<b>Description:</b> Code (Standard State/Province) as defined by appropriate government agency				
N403	116	<b>Postal Code</b>	O	ID	3/15	Used
		<b>Description:</b> Code defining international postal zone code excluding punctuation and blanks (zip code for United States)				

## Syntax Rules:

1. C0605 - If N406 is present, then N405 is required.

## Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

# Loop PO1

<b>Pos: 010</b>	<b>Repeat:</b> 100000
<b>Mandatory</b>	
<b>Loop: PO1 Elements: N/A</b>	

**User Option (Usage):** Must use

To specify basic and most frequently used line item data

## Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	PO1	Baseline Item Data	M	1		Must use
040		Loop CTP	O		1	Used

# PO1 Baseline Item Data

Pos: 010	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 10

**User Option (Usage):** Must use

To specify basic and most frequently used line item data

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	<b>Assigned Identification</b>	O	AN	1/20	Used
		<b>Description:</b> Alphanumeric characters assigned for differentiation within a transaction set				
PO102	330	<b>Quantity Ordered</b>	M	R	1/15	Must use
		<b>Description:</b> Quantity ordered				
PO103	355	<b>Unit or Basis for Measurement Code</b>	M	ID	2/2	Must use
		<b>Description:</b> Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		<b>Code Name</b>				
		EA	Each			
PO104	212	<b>Unit Price</b>	M	R	1/14	Must use
		<b>Description:</b> Price per unit of product, service, commodity, etc.				
PO106	235	<b>Product/Service ID Qualifier</b>	M	ID	2/2	Must use
		<b>Description:</b> Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<b>Code Name</b>				
		IB	International Standard Book Number (ISBN)			
		VP	Vendor's (Seller's) Part Number			
PO107	234	<b>Product/Service ID</b>	M	AN	1/30	Must use
		<b>Description:</b> Identifying number for a product or service				
PO108	235	<b>Product/Service ID Qualifier</b>	M	ID	2/2	Must use
		<b>Description:</b> Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<b>Code Name</b>				
		BP	Buyer's Part Number			
PO109	234	<b>Product/Service ID</b>	M	AN	1/30	Must use
		<b>Description:</b> Identifying number for a product or service				
PO110	235	<b>Product/Service ID Qualifier</b>	X	ID	2/2	Used
		<b>Description:</b> Code identifying the type/source of the descriptive number used in Product/Service ID (234)				

		<u>Code</u>	<u>Name</u>				
		UP	U.P.C. Consumer Package Code (1-5-5-1)				
PO111	234	<b>Product/Service ID</b>		X	AN	1/48	Used
<b>Description:</b> Identifying number for a product or service							

### Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

### Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

# Loop CTP

Pos: 040	Repeat: 1
Optional	
Loop: CTP	Elements: N/A

User Option (Usage): Used

To specify pricing information

## Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
040	CTP	Pricing Information	O	1		Used

# CTP Pricing Information

Pos: 040	Max: 1
Detail - Optional	
Loop: CTP	Elements: 2

User Option (Usage): Used

To specify pricing information

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTP02	236	<b>Price Identifier Code</b>	X	ID	3/3	Used
<b>Description:</b> Code identifying pricing specification						
<b>Code Name</b>						
MSR Manufacturer's Suggested Retail						
CTP03	212	<b>Unit Price</b>	X	R	1/17	Used
<b>Description:</b> Price per unit of product, service, commodity, etc.						

## Syntax Rules:

1. P0405 - If either CTP04 or CTP05 is present, then the other is required.
2. C0607 - If CTP06 is present, then CTP07 is required.
3. C0902 - If CTP09 is present, then CTP02 is required.
4. C1002 - If CTP10 is present, then CTP02 is required.
5. C1103 - If CTP11 is present, then CTP03 is required.

## Semantics:

1. CTP07 is a multiplier factor to arrive at a final discounted price. A multiplier of .90 would be the factor if a 10% discount is given.
2. CTP08 is the rebate amount.

## Comments:

1. See Figures Appendix for an example detailing the use of CTP03 and CTP04.
2. See Figures Appendix for an example detailing the use of CTP03, CTP04 and CTP07.

---

# Loop CTT

Pos: 010	Repeat: 1
Optional	
Loop: CTT	Elements: N/A

**User Option (Usage):** Must use

To transmit a hash total for a specific element in the transaction set

## Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	CTT	Transaction Totals	O	1		Must use

# CTT Transaction Totals

Pos: 010	Max: 1
Summary - Optional	
Loop: CTT	Elements: 1

**User Option (Usage):** Must use

To transmit a hash total for a specific element in the transaction set

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

**Description:** Total number of line items in the transaction set

## Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

## Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

# SE Transaction Set Trailer

Pos: 030	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

**User Option (Usage):** Must use

To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

## Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	<b>Number of Included Segments</b>	M	NO	1/10	Must use
<b>Description:</b> Total number of segments included in a transaction set including ST and SE segments						
SE02	329	<b>Transaction Set Control Number</b>	M	AN	4/9	Must use
<b>Description:</b> Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

## Comments:

1. SE is the last segment of each transaction set.

# Appendix

## All Included Elements in All Included Segments

<u>Id</u>	<u>Elements</u>	<u>Used in Segments</u>
19	City Name	N4
28	Group Control Number	GE, GS
66	Identification Code Qualifier	N1
67	Identification Code	N1
92	Purchase Order Type Code	BEG
93	Name	N1, PER
96	Number of Included Segments	SE
97	Number of Transaction Sets Included	GE
98	Entity Identifier Code	N1
116	Postal Code	N4
124	Application Receiver's Code	GS
128	Reference Identification Qualifier	N9
142	Application Sender's Code	GS
143	Transaction Set Identifier Code	ST
156	State or Province Code	N4
166	Address Information	N3
212	Unit Price	CTP, PO1
234	Product/Service ID	PO1
235	Product/Service ID Qualifier	PO1
236	Price Identifier Code	CTP
324	Purchase Order Number	BEG
329	Transaction Set Control Number	SE, ST
330	Quantity Ordered	PO1
337	Time	GS
350	Assigned Identification	PO1
353	Transaction Set Purpose Code	BEG
354	Number of Line Items	CTT
355	Unit or Basis for Measurement Code	PO1
364	Communication Number	PER
365	Communication Number Qualifier	PER
366	Contact Function Code	PER
369	Free-form Description	N9
373	Date	BEG, DTM, GS
374	Date/Time Qualifier	DTM
387	Routing	TD5
455	Responsible Agency Code	GS
479	Functional Identifier Code	GS
480	Version / Release / Industry Identifier Code	GS
563	Sales Requirement Code	CSH
933	Free-Form Message Text	MSG
101	Authorization Information Qualifier	ISA

<b><u>Id</u></b>	<b><u>Elements</u></b>	<b><u>Used in Segments</u></b>
I02	Authorization Information	ISA
I03	Security Information Qualifier	ISA
I04	Security Information	ISA
I05	Interchange ID Qualifier	ISA
I06	Interchange Sender ID	ISA
I07	Interchange Receiver ID	ISA
I08	Interchange Date	ISA
I09	Interchange Time	ISA
I10	Interchange Control Standards Identifier	ISA
I11	Interchange Control Version Number	ISA
I12	Interchange Control Number	IEA, ISA
I13	Acknowledgment Requested	ISA
I14	Usage Indicator	ISA
I15	Component Element Separator	ISA
I16	Number of Included Functional Groups	IEA